

SWIT®

4 × 6A CH SUPER FAST CHARGER

PC-P460A/S



SAVE 60% CHARGING TIME



3.5-inch Color LCD Display

Ready for mounting battery

1 **READY** Please put on battery.

2 **62%** Capacity percentage
Progress bar
CURRENT 5.95A
VOLTAGE 15.22V
Charging current
Realtime voltage

3 **E03Δ** Battery over heat.

4 **89%** Realtime capacity*
BATTERY 17889mAh
CYCLE 005
Battery cycle times*
(*SMBUS Digital battery only)

Charging abnormal Warning
(Following on-screen instructions to take steps)

Charging time Compare

SWIT Over 160Wh batteries - **6A Charging**
All Other batteries - **3A Charging**

Battery Capacity	2A normal Charger	3A Fast Charger	PC-P460A/S 6A Super Fast
160Wh	6h20m	4h15m ↓	2h35m ↓↓
220Wh	8h30m	6h15m ↓	3h30m ↓↓
260Wh	9h55m	7h10m ↓	4h15m ↓↓
290Wh	10h30m	7h40m ↓	4h50m ↓↓

↓↓ Save up to 60% charging time comparing to normal charger

Specifications

Model	PC-P460A	PC-P460S
Type	Gold mount	V-mount
Input	100~240VA, 50/60Hz	
Power	450W (Max)	
Charging output	16.8V, 3A/6A×4	
Working temp	0~40°C	
Working humidity	10%~90%RH	
Dimensions	330×135.6×162mm	330×153×162mm
Net weight	Approx. 2.43kg	


SWIT Electronics Co., Ltd.
+86-25-85805753
<http://www.swit.cc>
Email: contact@swit.cc

SWIT Electronics America, Inc
1-(408)260-8258
<http://www.swit.us>
Email: info@swit.us

SWIT Electronics Europe GmbH
+49(0)20659799339
<http://www.swit-europe.com>
Email: info@swit-europe.com



Facebook Page



Instagram